





## Complete Bright-VU Specifications:

|                              |   |
|------------------------------|---|
| <b>Number of Indicators:</b> | 20 bar type LEDs                          |
| <b>Colors:</b>               |   |
| -35 dB thru -1 dB            | Green                                     |
| 0 dB                         | Yellow                                    |
| +1 dB thru +3 dB             | Orange                                    |
| +6 dB thru +18 dB            | Red                                       |
| <b>Basic Accuracy:</b>       | .1 dB                                     |
| <b>Analog Input:</b>         |   |
| Sensitivity                  | -10 to +24 dBU for full scale             |
| Sensitivity Adjustment       | Screwdriver adjustment on rear panel      |
| Overload Level               | +24 dBm                                   |
| Impedence                    | 40K Ohm balanced/ 20K Ohm unbalanced      |
| CMRR                         | -90 dB                                    |
| Connector                    | 3-pin XLR                                 |
| <b>Digital Input:</b>        |   |
| Codes                        | AES/EBU, S/PDIF                           |
| Impedence/ Connector         | 110 Ohm balanced (XLR female)             |
| Loop-through                 | 2200 Ohm balanced (XLR male)              |
| <b>Response Time:</b>        |   |
| VU Mode                      | 300mS / 20 dB attack & release            |
| Peak Mode                    | 0mS attack, 2.8 Sec / 24dB release        |
| <b>Frequency Response:</b>   | +/- .1 dB (20 Hz to 20 Khz)               |
| <b>Power Requirement:</b>    |   |
| BV2 & BDT                    | 115/230VAC switchable, 50/60hz / 5 watts  |
| BV4                          | 115/230VAC switchable, 50/60hz / 10 watts |
| BV6                          | 115/230VAC switchable, 50/60hz / 15 watts |
| <b>Dimensions:</b>           |   |
| BV2,BV4,BV6 (1RU)            | 19" W x 7" D x 1 3/4" H                   |
| BDT (Desktop)                | 6" W x 6 1/4" D x 2 1/2" H                |

BDT




BV2



BV4



BV6



Standard Scale  
(shown full size)

-35 -30 -25 -20 -15 -10 -7 -5 -3 -2 -1 0 +1 +2 +3 +6 +9 +12 +15 +18

-35 -30 -25 -20 -15 -10 -7 -5 -3 -2 -1 0 +1 +2 +3 +6 +9 +12 +15 +18

### Bright-VU Models

- BDT-• Single stereo (desktop)
- BV2-•✓ Single stereo (1RU)
- BV4-•✓ Dual stereo (1RU)
- BV6-•✓ Triple stereo (1RU)

- Must specify "A" for analog or "D" for digital
- ✓ "O" for alarm output (call for details)

Logitek

5622 Edgemoor Drive  
Houston, TX 77081  
800.231.5870 (North America)  
(Tel) 713-664-4470 (Fax) 713-664-4479