

# 500ADA

## Analog Video Distribution Amplifier

1

2

3

4

5

6

7

8

9

10

11

12

13





### ► Features & Benefits

- 75Ω or high impedance input (jumper selectable)
- High common mode range and common mode rejection ratio (CMRR)
- Gain control
- Jumper selectable AC or DC coupling
- Looping feature with external "T" connector
- Consistent input impedance if card power is lost
- VistaLINK® -capable for remote monitoring via SNMP (using VistaLINK® PRO) when installed in 500FR frame with 500FC VistaLINK® Frame Controller

The 500ADA is housed in the 3RU 500FR **exponent** frame that will hold up to 16 modules.

### Card Edge LEDs

- Module status/Local Fault
- Power supply status



### ► Specifications

#### Analog Video Input:

Standards: Any analog video format, up to 2V p-p and 30MHz bandwidth  
Connector: 1 BNC per IEC 61169-8 Annex A  
Common mode range:  
CMRR: > 70dB to 1kHz  
Signal amplitude: 2.5V p-p max  
Impedance: 75Ω terminated, 35kΩ Hi-Z (jumper selectable)  
Coupling: AC or DC (jumper selectable)  
Return loss: > 40dB to 10MHz, > 30dB to 30MHz

#### Analog Video Outputs:

Number of Outputs: 9 Per Card  
Connector: BNC per IEC 61169-8 Annex A  
Output impedance: 75Ω  
Gain control range: ±5dB  
Freq. Response: < ±0.05dB (to 5.5MHz)  
Differential Gain: < 0.17%  
Differential Phase: < 0.19°  
C/L gain inequality: < ±0.1%  
C/L Delay: < ±2ns  
Output isolation: 42dB to 10MHz, 32dB to 30MHz  
Output return loss: > 40dB to 30MHz  
Noise performance: < -78dB RMS NTC7 weighting  
< -70dB RMS 15kHz to 5.5MHz

#### Electrical:

Voltage: +12V DC  
Power: 1.2W  
EMI/RFI: Complies with FCC Part 15 Class A, EU EMC Directive

#### Physical:

Number of Slots: 1

### ► Ordering Information

**500ADA**

Analog Video Distribution Amplifier (1x9)

**Enclosures****500FR**  
**S501FR****exponent**Compact High Density Distribution Frame  
Standalone enclosure