

7702BPX-IF, 7703BPXA-IF

2x1 RF Protection Switch for IF Frequencies



The 7702BPX-IF and 7703BPXA-IF 2x1 RF protection switches for IF frequencies provide automatic changeover functionality to provide bypass protection for RF signals from 10MHz to 850MHz. Typical applications include main/standby failover protection for 70/140MHz uplink applications.


The 7703BPXA-IF has integrated VistaLINK® technology for remote control and monitoring capability via SNMP. This provides the ability to locally or remotely configure and monitor parameters such as module status, selected input, power level and switching threshold.

When used for automatic changeover, the 7702BPX-IF and 7703BPXA-IF have a MAIN input and a STANDBY input. It will automatically switch to the Standby input when the Main input power is weak or lost. Switch back to the Main input when the signal is re-established may be configured to happen automatically or manually. The 7702/7703BPX-IF may also be configured to operate manually as a 2:1 switch, which may be controlled locally or remotely via GPI or SNMP (7703 model only).

The 7702BPX-IF and 7703BPXA-IF occupy one card slot and can be housed in a 1RU frame that will hold up to 3 modules, a 3RU frame that will hold up to 15 modules, a 350FR portable frame that will hold up to 7 modules or a standalone enclosure which holds 1 module.

►Features & Benefits

- Wide operating frequency range, 10MHz to 850MHz
- Intelligent auto switching with input power detection
- User-definable threshold levels on 7703BPXA-IF version
- Maintains switch state and RF channel on loss of power to card or frame
- Supports automatic or manual control via GPI or SNMP on 7703BPXA-IF
- Switch state indication via GPO
- Card edge LEDs indicate active input channels, output channel and power levels below threshold
- Fully hot-swappable from front of frame
- Comprehensive signal and card status monitoring via four digit card edge display or remotely through SNMP and VistaLINK® on 7703 version
- VistaLINK® capability is available when 7703BPXA-IF modules are used with the 3RU 7800FR or 350FR portable frame and a 7700FC VistaLINK® Frame Controller module in slot 1 of the frame



►Specifications

RF Input/Output:	General Purpose Inputs:	General Purpose Outputs:
Inputs: 2	Number of Inputs: 2	Number of Outputs: 1
Outputs: 1	Type: Opto-isolated, active low with internal pull-ups to +5V	Type: "Dry Contact" relay contacts -normally open & normally closed contact provided
Connector: 1 BNC per IEC 61169-8 Annex A (F-type and SMA optional)	Connector: 2 pins plus ground on 6-pin terminal strip	Connector: 3 pins on 6-pin terminal strip
I/O Impedance: 75Ω, 50Ω optional	Signal Level:	Electrical:
Frequency Response:	+5V Pullup: Low: -5 to +2.5V DC, High: 3.5 to 10V DC	Voltage: +12V DC
10-200MHz: < ±0.25dB	+12V Pullup: Low: -5 to +9.5V DC, High: 10.5 to 15V DC	Power: 3W
10-850MHz: < ±0.5dB	Max Sink Current: (input shorted to ground) 15 mA	Physical (number of slots):
Insertion Loss: < 4dB	Max Leakage Current for input High: 200μA	350FR: 1
Return Loss:		7700FR-C: 1
10-200MHz: < 15dB		7800FR: 1
10-850MHz: < 17dB		
Isolation: > 50dB (10-850MHz)		
Input Power Range: 0dBm to -50dBm		

►Ordering Information

7702BPX-IF	2x1 RF Protection Switch for IF Frequencies
7703BPXA-IF	2x1 RF Protection Switch for IF Frequencies, with VistaLINK® monitoring
7702BPX-IF-B50	2x1 RF Protection Switch for IF Frequencies, 50Ω BNC connectors
7703BPXA-IF-B50	2x1 RF Protection Switch for IF Frequencies, 50Ω BNC connectors, with VistaLINK® monitoring
7702BPX-IF-S50	2x1 RF Protection Switch for IF Frequencies, 50Ω SMA connectors
7703BPXA-IF-S50	2x1 RF Protection Switch for IF Frequencies, 50Ω SMA connectors, with VistaLINK® monitoring

Ordering Options Rear Plate and optional connector type must be specified at time of order
Eg: Model +3RU (if 75Ω F-type connector required, order optional +F75)

Rear Plate Suffix	
+3RU	3RU Rear Plate for use with 350FR, 7700FR-C or 7800FR Multiframe
+1RU	1RU Rear Plate for use with 7701FR Multiframe
+SA	Standalone Enclosure Rear Plate
Connector Suffix	
+F75	75Ω, F-Type Rear Connector

Enclosures	
350FR	3RU Portable Multiframe which holds up to 7 single slot modules
7700FR-C	3RU Multiframe which holds up to 15 single slot modules
7800FR	3RU Multiframe which holds up to 15 single slot modules
7701FR	1RU Multiframe which holds up to 3 single or dual slot modules
S7701FR	Standalone Enclosure