



SEARCH

- [Field LCD Monitor](#)
- [Rack-Mount Monitor](#)
- [Studio Monitor](#)
- [Power Station Box](#)
- [V-Mount Battery](#)
- [Gold-Mount Battery](#)
- [NP-1 Style Battery](#)
- [Charger / Adaptor](#)
- [Converter/Distributor](#)
- [Fiber Camera System](#)
- [Wireless Transmission System](#)
- [LED Light](#)
- [Battery for Sony](#)
- [Battery for Panasonic](#)
- [Battery for Canon](#)
- [Battery for JVC](#)
- [Accessories](#)
- [Gra-Vue Products](#)
- [AViPAS Products](#)
- [B-Stock & Clearance](#)
- [Dealers/ Rentals](#)
- [Sales Reps](#)
- [Shipping & Returns](#)
- [Material Safety Data Sheets](#)
- [FAQ](#)

[Home](#) > [Power Station Box](#) > S-4010 Power Station Box (12v + 12v)

S-4010 Power Station Box (12v + 12v)



Item# S-4010
\$670.00
Availability: Usually ships in 2-3 weeks

Product Description



Long-lasting power solution for high draw devices

S-4010 power station box can install 4 pieces of V-mount batteries which can provide more power and longer power supply time comparing to single Li-ion battery. It can meet the demand of different users, and is very suitable for Cine cameras, lightings for Film & Television and mobile studios.

Key Features:

- PP+ Fiber glass case, strong and durable
- Install 4 x V-mount batteries
- 2-ch 4-pin XLR DC output
- LED panel to display real-time voltage and low voltage warning
- Charging without take out batteries by provided 4-pin XLR DC charging socket
- Intelligent protective circuit design, safe and reliable

Specification:

Input	DC 16.8V 5A (charging)
Output	DC 11-16.8V 15A x2 (180W x2)
Working temperature	0℃~+40℃
Working humidity	10%~90%
Storage temperature	-15%~+60%
Dimensions	290mm x 221mm x 278mm
Weight	Approx. 3.45kg

PP+ Fiber glass case, strong and durable

S-4010 adopts PP+ Fiber glass case which is high intensity, high toughness and high temperature resistant.



Power with 4 V-lock batteries, portable and usable

Considering the size, weight, power efficiency, and usability, S-4010 is designed to be powered with 1-4 V-lock batteries, which are widely used and easy to find. S-4010 is compatible with all the SWIT V-lock batterie, or 3rd party batteries with dimensions less than 168(L)x101(W)x65(H)mm.




Auto-balanced circuit design

With auto-balanced circuit, S-4010 can be powered by 1-4 batteries, with different capacity. The max output is limited by the batteries output.

2-ch 4-pin XLR DC output

With 2-ch 4-pin XLR output sockets, S-4010 is capable of outputting 2-ch 11-16.8V, max 15A power simultaneously. And S-4010 is designed with multiple circuit protections, such as over load, over voltage, and etc.



LED panel display status

With a LED panel, S-4010 can display real-time voltage, and when battery capacity is too low, the LED panel will keep flashing to remind you to change or charge batterie.



Charging without taking out batteries

With the supplied 5A charger, user can charge the batteries in the S-4010 directly, without taking out of them.



Cooling fan design

The fan keeps dissipating heat from the box, and makes it safe when working in high temperature environment.



Warranty Period: Two years conditional.

Related Items:

[S-3840S: 160Wh Heavy Duty Digital Battery Pack](#)

User Manual:

[S-4010 User Manual](#)

