

BL-300 | 300W Bowens Mount COB LED Light



- > 300W ultra bright 5600K COB-LED
- > 54000Lux @ 1m with reflector
- > CRI Ra 97, TLCI 98
- > Standard Bowens Mount, various accessories
- > Separate control box, AC and dual batteries power
- > 0-100% flick-free dimming
- > 9 presets light effects with speed adjustment
- > DMX512 5pin XLR input & output
- > LCD display dimmer, light effect and DMX
- > Support IOS/Android APP control

MSRP Ex TAX / Shipping

- Features | Specifications | Download | What's in box | Optional accessory | Related



Bowens COB-LED Light

BL-300 is a Bowens mount 300W COB LED light, with DMX control, high CRI/TLCI, accurate color performance, and various Bowens accessories for broadcast studio, mobile studio, live streaming studio applications.



54000Lux @1m Ultra Bright



BL-300 adopts ultra bright 300W COB-LED, 5600K daylight only, provides 54000Lux illuminance at 1 meter distance with standard reflector.

BL-300	1 meter	3 meters	5 meters
Light only	12100Lux	1570 Lux	650Lux
With Reflector	54000Lux	7020Lux	2910Lux

Accurate Color Render

CRI 97; TLCI 98

The normal LED light has 80-85 CRI or TLCI, while BL-300 offers the super high CRI at 97 and TLCI at 98, and will not shift the object original colors under light.



Separated Control Box

AC & Batteries Power, DMX IN & OUT

BL-300 separates the control box to the light head, to enable power by batteries for outdoor lighting. The control box has PowerCON AC input, 2x V-mount battery plates, DC connector with light head, 5-pin DMX in & out, control buttons and LCD display.

Dual Batteries Installation

BL-300 control box can be fixed to 25-45mm light stand, and quickly released by a V wedge structure, which is strong enough for 2x large capacity batteries.




Various Bowens Accessories

BL-300 provides various Bowens mount light shape accessories, including quick setup octagonal softbox, lantern softbox, parabolic dome softbox, and beauty dish, snoot, fresnel lens ect, for optional purchase.



9x Light Effects

BL-300 has built-in 9x demo effects, including the commonly used car lights, candles, lightning, flash light effects, for creative productions.




Smart Phone APP Control

IOS and Android

BL-300 and its series model BL-150E, BL-200, can be connected to smart phone by bluetooth, and you can rename and group the lights, adjust dimmer, select light effects and sync the light effect to a music in your device.

IOS APP: App Store, search "DeSal Lite+"
Android APP: Download HERE.



SWIT®

Bowens Mount COB-LED Lights

BL-series



BL-150E

150W AC Power Only, Built-in Controller



BL-200

200W AC & Battery Power, Separate Controller



BL-300

300W AC & Battery Power, Separate Controller



Ultra Bright COB LEDs

5600K Daylight

		1 meter	3 meters	5 meters
BL-150E	Light only	4400Lux	570 Lux	240Lux
	With Reflector	27290Lux	3550Lux	1470Lux
BL-200	Light only	5900Lux	770Lux	320Lux
	With Reflector	38000Lux	4940Lux	2050Lux
BL-300	Light only	12100Lux	1570Lux	650Lux
	With Reflector	54000Lux	7020Lux	2910Lux




CRI 97; TLCI 98

Accurate Color



Sector	Lightness	Chroma	Hue
R	0	0	0
R/Y	0	0	0
Y	0	0	0
Y/G	0	0	0
G	0	0	0
G/C	0	0	+
C	0	0	0
C/B	0	0	0
B	0	-	0
B/M	0	0	+
M	0	0	+
M/R	0	0	+



Control Panel

5-pin DMX in & out



5-pin DMX IN PowerCON AC IN 5-pin DMX OUT

BL-150E



BL-200 / 300 Controller

Control buttons

Power Out to light head

PowerCON AC-IN


5-pin DMX OUT

5-pin DMX IN




APP Remote


iOS & Android




Add and Group lights



Intensity adjust



Select light effects



Sync to music



9x Light Effects

With Intensity and Speed Adjustment



Lightning Lightning Screen Candle Flash Strobe Car light Alarm Breath



Bowens Mount Accessories

Optional Purchase




BA-OCT36

36-inch Easy-open Octagonal Softbox
With dual diffusers



BA-LAN26

26-inch Easy-open Lantern Softbox



BA-PARA26

26-inch Easy-open Parabolic Dome Softbox
With eggcrate and dual diffusers



BA-BD16

16-inch Beauty Dish
with 40° Honeycomb and diffuser



BA-ST3

3.1-inch Snoot with honeycomb
with 25° & 30° Honeycombs and 5x color filters



BA-F3X

Fresnel 12-40° 3x Lens
with 10x color filters



Specifications

Model	BL-150E	BL-200	BL-300
LED	150W COB-LED	200W COB-LED	300W COB-LED
Luminance	27290Lux @ 1m with reflector	38000Lux @ 1m with reflector	54000Lux @ 1m with reflector
Color temp	5600K	5600K	5600K
Color rendering	CRI 97; TLCI 98	CRI 97; TLCI 98	CRI 97; TLCI 98
DMX	DMX512 5pin XLR in & out	DMX512 5pin XLR in & out	DMX512 5pin XLR in & out
Input voltage	AC 100-240V (PowerCON)	AC 100-240V (PowerCON), battery 11-17V	AC 100-240V (PowerCON), battery 11-17V
Dimension	272×199×333mm	Light: 272×199×333mm Controller: 170×125×218mm	Light: 301×199×333mm Controller: 170×125×218mm
Weight	2.15kg	Light 1.8kg; Controller 1.9kg	Light 2.5kg; Controller 1.9kg


SWIT Electronics Co., Ltd.
+86-25-85805753
<http://www.swit.cc>
Email: contact@swit.cc

SWIT Electronics America, Inc
1-(408)260-8258
<http://www.swit.us>
Email: info@swit.us

SWIT Electronics Europe GmbH
+49(0)2131 6632331
<http://www.switeu.com>
Email: info@swit-europe.com



Facebook Page



Instagram















