


Home > Battery > DV

LB-SU98 | SONY BP-U Camcorder Battery Pack



- ◆ 14.4V nominal voltage Li-ion battery
- ◆ Compatible with SONY BP-U batteries
- ◆ Display remaining power info in camera
- ◆ 98Wh / 6.8Ah capacity
- ◆ Built-in 14.4V D-tap output / Charging input
- ◆ Built-in 5V/2A USB output
- ◆ 4-level LED power indicator
- ◆ Multiple circuit protections



 MSRP Ex TAX / Shipping

[Features](#) [Specifications](#) [Download](#) [What's in box](#) [Optional accessory](#) [Related](#)



SONY BP-U type Battery

LB-SU98 is the replacement battery for Sony BP-U60, compatible with SONY Camcorder PXW-FX9 / FS7 / FS5, PXW-Z280 / Z190 / X280.



98Wh / 6.8Ah High Capacity

With 14.4V nominal voltage, the LB-SU98 has 98Wh / 6.8Ah capacity, and can run approx. 3 hours on SONY PXW-FX9 camera.

Built-in D-tap DC Output Socket

A D-tap DC output socket is equipped on the side of LB-SU98 battery, for DC14.4V (Nominate) connection. You can connect on-camera LED light, monitor or wireless transmitter on the D-tap socket, and get power simultaneously with camera. The Max power from D-tap is 70W, 6A. The D-tap socket can also be used as charging input, by SWIT portable charger PC-U130B/B2.



Built-in 5V/1A USB Socket

Connect your USB devices like smart phone or pad to the USB socket of LB-SU98, press the power check button, and then the battery will start to output 5V/2A power to charge your devices.

LED Power Indicator

The LB-SU98 battery has the 4-level LED power indicators to check the battery remaining capacity. You can get a quick view of capacity before using. The power check button can also be used to trigger USB charging.



Easy Charging

The LB-SU98 can be charged on SWIT 2-ch charger S-3602U or 4-ch charger LC-D421. And you can also use SWIT PC-U130B/B2 Portable D-tap Charger for LB-SU98. By S-3602U/LC-D421 will take about 4 hours and 30 minutes to charge from empty to 100%. By PC-U130B/B2 will take 2 hours and 50 minutes to fully charge.

SWIT®

BP-U type Li-ion Battery Pack



LB-SU75 75Wh



LB-SU98 98Wh



Features:

- ◆ Compatible with
SONY PXW-Z280 / Z190 / X280
SONY PXW-FS5 / FS7 / FX9
- ◆ Display remaining power in viewfinder
- ◆ 14.4V D-tap DC output
- ◆ 5V/2A USB power output
- ◆ 4-level LED power indicators



14.4V D-tap output



5V/2A USB output

Specifications:

| Model | LB-SU75 | LB-SU98 | |
|-----------------|---------------|---------------|---------------|
| Nominal Voltage | 14.4V | 14.4V | |
| Capacity | 75Wh, 5200mAh | 98Wh, 6800mAh | |
| Dimension | 70×42×96mm | 70×42×96mm | |
| Net weight | 430g | 464g | |
| Load | Pins | 50W, 4A | 70W, 6A |
| | D-tap | 50W, 4A | 70W, 6A |
| | USB | 10W (5V / 2A) | 10W (5V / 2A) |
| | Total | 50W, 4A | 70W, 6A |

Compatible Cameras:

| Camera models | Compatibility |
|-------------------------|---------------|
| SONY PXW-FX9 | ✓ |
| SONY PXW-Z280 | ✓ |
| SONY PXW-Z190 | ✓ |
| SONY PXW-FS7 | ✓ |
| SONY PXW-FS5 | ✓ |
| SONY PXW-X280 | ✓ |
| SONY PXW-X160/X180/X200 | ✗ |
| SONY PMW-EX1/1R/3/F3 | ✗ |



LB-SU98

SWIT®

100% 75% 50% 25%





LB-SU98

SWIT®

MAX
3.5A

D-TAP

