

75Ω BNC Crimp Plugs

■ BCP-A Series (Straight Type) **NEW**

VSWR 1.1 @ 2GHz, VSWR 1.2 @ 3GHz


Model	Suitable Cable		Center Pin	Sleeve	Boot	Die Set
	Canare	Belden (suggested)				
BCP-A25	L-2.5C2V	—	★ BN1018A	★ BN7029C	CB02	TCD-35CA
BCP-A25F	L-2.5CFB	1855A, 8218, 1417B, 1418B	B11014E	★ BN7029C	CB02	TCD-35CA
BCP-A3	L-3C2VS, L-3C2V, V*-3C	—	B11014E	BN7003A	CB03	TCD-35CA
★ BCP-A31	L-3C2W	—	B11014E	★ BN7011	CB04	TCD-31C
BCP-A32	—	1506A, 1824A, 1825A, 1826A, 643948	B11016E	★ BN7026A	CB03	TCD-35CA
BCP-A3F	L-3CFB, LS-3CFB, V*-3CFB	—	B11015E	BN7003A	CB03	TCD-35CA
BCP-A4	LV-61S	8241, 8279, RG-59B/U	B11015E	BN7015A	CB04	TCD-4CA, TCD-451CA
BCP-A42	—	1505F	B11016E	★ BN7011	CB04	TCD-31C
BCP-A4F	L-4CHD, L-4CFB, LS-4CFB, V*-4CFB	1505A, 8212, 8241F, 9167, 9259, 9659	B11016E	BN7015A	CB04	TCD-4CA, TCD-451CA
BCP-A5	L-5C2VS, L-5C2V, V*-5C	—	B11016E	BN7016	CB05A	TCD-35CA
BCP-A52	L-5C2W	—	B11016E	★ BN7014	—	TCD-451CA
BCP-A55	—	1695A, 89120, 87120, 633948, 9116P	B11020D	★ BN7045A	CB05A	TCD-35CA
BCP-A5F	L-5CFB, LS-5CFB, V*-5CFB	—	B11020D	B75004A	CB05A	TCD-35CA
BCP-A77	LV-77S	8281F	B11016E	B75004A	CB05A	TCD-5CF-TCD-55FA
BCP-VA3	V*-3C	—	B11014E	★ BN7052A	CB02	TCD-35CA
BCP-VA5	V*-5C	—	B11016E	★ BN7045A	CB05A	TCD-35CA

• Standard package (20pcs/100pcs).

★ Production by order. Please ask us for ordering lot.



BCP-A3



Return loss for BCP-A3

■ BCP-C Series (Straight Type)

VSWR 1.1 @ 2GHz


Model	Suitable Cable		Center Pin	Sleeve	Boot	Die Set
	Canare	Belden (suggested)				
BCP-C1	L-1.5C2VS, V*-1.5C	83264, 83267	Solder	★ BN7022	CB01	TCD-1DB
★ BCP-C5HD	L-5CHD	—	★ BN1139	B75004A	CB05A	TCD-5HD
BCP-C6HD	L-6CHD	—	★ BN1083A	★ BN7074A	—	TCD-67HD
BCP-C71A	—	7731A, 9064, 9292, 1617A, 9011	★ BN1043A	★ BN7021A	—	TCD-7CA
BCP-C7FA	L-7CFB	—	★ BN1012B	★ BN7021A	—	TCD-7CA
BCP-C7HD	L-7CHD	—	★ BN1082A	★ BN7021A	—	TCD-67HD

• Standard package (20pcs/100pcs).

★ Production by order. Please ask us for ordering lot.



BCP-C6HD



Return loss for BCP-C6HD

■ BCP-LC Series (Right Type)

VSWR 1.1 @ 2GHz

Model	Suitable Cable		Center Pin	Sleeve	Boot	Die Set
	Canare	Belden (suggested)				
BCP-LC3	L-3C2VS, L-3C2V, V*-3C	—	B11014E	BN7003A	—	TCD-35CA
BCP-LC3F	L-3CFB, LS-3CFB, V*-3CFB	—	B11015E	BN7003A	—	TCD-35CA
BCP-LC5	L-5C2VS, L-5C2V, V*-5C	—	B11016E	BN7016	—	TCD-35CA
BCP-LC5F	L-5CFB, LS-5CFB, V*-5CFB	—	B11020D	B75004A	—	TCD-5CF, TCD-55FA

• Standard package (20pcs)



BCP-LC3

- High performance of 1.1 or less VSWR up to 2GHz. (Excluding BCP-A25, BCP-A25F, BCP-A4 and BCP-C1)
- Position mark on body allows the connector fit to be checked easily.(Excluding BCP-C, BCP-LC series)

- Lock mechanism used on insulation improves reliability by preventing shifting or detaching of the contact pin.
- Gold plating on the contact pin prevents deterioration, even after years of use.

Be sure to use the Canare crimping tool for installing connectors on cables.

BCP-C/PC to BCP-B/A Upgrading Chart

BCP-PC	→	BCP-B	BCP-A
BCP-C1	→	N/A	
BCP-C25	→	—	BCP-A25
BCP-C25F	→	BCP-B26 (for 1855A)	BCP-A25F
BCP-C25HDA	→	BCP-B25HD	—
BCP-C31	→	—	BCP-A31
BCP-C32	→	—	BCP-A32
BCP-C3B	→	—	BCP-A3
BCP-C3F	→	BCP-B3F	BCP-A3F
BCP-C42	→	—	BCP-A42
BCP-C4B	→	—	BCP-A4
BCP-C4F	→	BCP-B4F	BCP-A4F
BCP-C52	→	—	BCP-A52
BCP-C53A	→	BCP-B53	—
BCP-C55A	→	—	BCP-A55
BCP-C5B	→	—	BCP-A5

BCP-PC	→	BCP-B	BCP-A
BCP-C5FA	→	BCP-B5F	BCP-A5F
BCP-C5HD	→	N/A	
BCP-C6HD	→	N/A	
BCP-C71A	→	N/A	
BCP-C77A	→	—	BCP-A77
BCP-C7FA	→	N/A	
BCP-C7HD	→	N/A	
BCP-VC3	→	—	BCP-VA3
BCP-VC5	→	—	BCP-VA5
BCP-PC3	→	—	BCP-A3
BCP-PC3F	→	BCP-B3F	BCP-A3F
BCP-PC4	→	—	BCP-A4
BCP-PC4F	→	BCP-B4F	BCP-A4F
BCP-PC5	→	—	BCP-A5
BCP-PC5F	→	BCP-B5F	BCP-A5F

The new BCP-B/A series will replace BCP-C/PC as the left chart. (!)

What's new for BCP-B and BCP-A?

BCP-B is specially designed for a particular coax cable to minimize return loss at 3GHz, and achieves industry-leading levels of performance at affordable price.

BCP-A extends a lot of advantages from BCP-C and BCP-PC such as RL26dB@2GHz, reasonable price, and so on.

(!): A different die set will fit between BCP-B5F and BCP-A5F