Log-in ▶

Home > Charger/Adaptor > V-mount

MATRIX-S8 | 8×100W Ultra fast V-mount Wall Charger



- > 8-ch simultaneous fast charging
- > Charge both 14.4V and 28.8V V-mount batteries
- > 100W/6A for SWIT 14.4V & ≥160Wh batteries
- > 100W/3A for SWIT 28.8V & ≥160Wh batteries
- > 50W/3A for other batteries
- > 2× 3.5-inch color LCD info display
- > Battery cycle times display > Large LED charging indicators
- > Wall mounting or 19-inch rack install













MSRP

Ex TAX / Shipping

Features

Specifications

Download

What's in box

Optional accessory

Related



8x100W Ultra Fast Wall Charger

MATRIX-S8 is an 8-ch simultaneous V-mount wall charger with 100W ultra fast charging speed each channel, save up to 60% charging time comparing to normal chargers, supports both 14.4V and 28.8V batteries, for TV stations and rental houses installation.

Charging time comparation

Battery Capacity	160Wh	210Wh	220Wh	290Wh	420Wh
33W normal charger	6h	8h	8h 15m	10h 30m	15h
50W fast charger	4h ↓	5h 15m↓	5h 45m ↓	7h 15m↓	10h 10m↓
MATRIX 100W Ultra fast charger	2h 15m ↓↓	3h ↓↓	3h 20m ↓↓	3h 50m ↓↓	5h 20m 👯
	2h 15m 👯	3h ↓↓	3h 20m↓↓	3h 50m ↓↓	5h 20m ↓

↓↓ Save up to 60% charging time






Lauarters

Flexible Wall Mounting Plate

MATRIX-S8 provides with a wall mounting plate on the backside, to be screwed onto the wall, or mounting to standard 19-inch rack bracket. You can even install the mounting plate onto storage rack or DIT cart.

3.5-inch Color LCD and Indicators

MATRIX-S8 provides 2x 3.5-inch color LCD to display charging progress, charging current, voltage, battery cycle times for each channel. You can also check the charging status by large charging indicators from a distance.



Heerdterbuschstrasse 10 / HALLE 9, 41460 Neuss, NRW Germany VAT: DE308323924 WEEE-Reg.-Nr. DE 37399843

SWIT Electronics Europe GmbH

Email: info@swit-europe.com

Email Newsletter

Please enter Email address below and subscribe our newsletters.

submit

Privacy Policy



SWIT®

MATRIX-S8

8×100W Ultra Fast Wall Charger


Charge both 14.4V and 28.8V batteries

SAVE 60% CHARGING TIME




Wall / Bracket Mounting

MATRIX-S8 provides a wall mounting plate to be screwed onto the wall, or mounting to standard 19-inch rack bracket. You can even install the mounting plate onto storage rack or DIT cart.





3.5-inch LCD and Indicators



Charging abnormal Warning (Following on-screen instructions to take steps) **Charging Status** Realtime Capacity / Cycle times



8×100W Ultra Fast Charging

Charge both 14.4V and 28.8V V-mount Batteries

Battery Capacity	33W Charger	50W fast Charger	100W Ultra Fast MATRIX
160Wh	6h	4h ↓	2h 15m 👯
210Wh	8h	5h 15m ↓	3h ‡ ‡
220Wh	8h 15m	5h 45m ↓	3h 20m ↓↓
290Wh	10h 30m	7h 15m ↓	3h 50m ↓↓
420Wh	15h	10h 10m ↓	5h 20m ↓↓



Specifications

Model	MATRIX-S8			
Туре	V-mount			
Input	100~240VA, 50/60Hz			
Power	900W (Max)			
	DC 16.8V, 6A (100W)×8 (SWIT 14.4V &≥160Wh batteries)			
Charging output	DC 33.6V, 3A (100W) ×8 (SWIT 28.8V &≥160Wh batteries)			
	DC 16.8V, 3A (50W) ×8 (Other batteries)			
Dimensions	630×436×89mm			
Net weight	Approx. 10.6kg			

SWIT Electronics Co., Ltd. +86-25-85805753

SWIT Electronics America, Inc 1-(408)260-8258 http://www.swit.cc http://www.switusa.com Email: contact@swit.cc Email: info@swit.us

SWIT Electronics Europe GmbH +49(0)21316632331 http://www.switeu.com Email: info@swit-europe.com







